

RFM Cable Manager Fill Capacity Chart

Cabinet VCM

Cable Type: Cat 6a

0.354" diam.

RFM Part Number	80% Fill	60% Fill	50% Fill	40% Fill	30% Fill
5_-VCM-FND	142	107	89	71	53
7_-VCM-FND	199	149	124	100	75
5_-VCM-F	142	107	89	71	53
7_-VCM-F	199	149	124	100	75
783-VCM-HD-36	356	267	222	178	133
790-VCM-HD-36	356	267	222	178	133
RFM-1083-HDC	975	732	610	488	366
RFM-1090-HDC	975	732	610	488	366
RFM-5_-VCM	132	99	83	66	50
RFM-7_-VCM-A	199	149	124	100	75
RFM-9_-VCM-A	225	168	140	112	84
RFM-6_VBB	102	76	64	51	38
RFM-7_VCM-HD	363	272	227	182	136
RFM-FORT-CMS	244	183	152	122	91
RFM-FORTA-CMS	244	183	152	122	91
RFM-DR-ADJ*	101 ~ 167	76 ~ 125	63 ~ 104	50 ~ 83	38 ~ 62
RFM-683-VCT-HD	101 ~ 167	76 ~ 125	63 ~ 104	50 ~ 83	38 ~ 62

of Cables # of Cables # of Cables # of Cables # of Cables

Cabinet VCM

Cable Type: Cat 6

0.250" diam.

RFM Part Number	80% Fill	60% Fill	50% Fill	40% Fill	30% Fill
5_-VCM-FND	285	214	178	143	107
7_-VCM-FND	399	299	250	200	150
5_-VCM-F	285	214	178	143	107
7_-VCM-F	399	299	250	200	150
783-VCM-HD-36	713	535	446	357	267
790-VCM-HD-36	713	535	446	357	267
RFM-1083-HDC	1956	1467	1222	978	733
RFM-1090-HDC	1956	1467	1222	978	733
RFM-5_-VCM	265	199	166	132	99
RFM-7_-VCM-A	399	299	250	200	150
RFM-9_-VCM-A	450	338	281	225	169
RFM-6_VBB	204	153	127	102	76
RFM-7_VCM-HD	728	546	455	364	273
RFM-FORT-CMS	489	367	306	244	183
RFM-FORTA-CMS	489	367	306	244	183
RFM-DR-ADJ*	204 ~ 336	153 ~ 252	127 ~ 210	102 ~ 168	76 ~ 126
RFM-683-VCT-HD	204 ~ 336	153 ~ 252	127 ~ 210	102 ~ 168	76 ~ 126

of Cables # of Cables # of Cables # of Cables # of Cables

Cabinet VCM

Cable Type: Cat 5e

0.187" diam.

RFM Part Number	80% Fill	60% Fill	50% Fill	40% Fill	30% Fill
5_-VCM-FND	510	382	319	255	191
7_-VCM-FND	714	535	446	357	268
5_-VCM-F	510	382	319	255	191
7_-VCM-F	714	535	446	357	268
783-VCM-HD-36	1274	956	797	637	478
790-VCM-HD-36	1274	956	797	637	478
RFM-1083-HDC	3496	2622	2185	1748	1311
RFM-1090-HDC	3496	2622	2185	1748	1311
RFM-5_-VCM	473	355	296	237	178
RFM-7_-VCM-A	714	535	446	357	268
RFM-9_-VCM-A	805	604	503	402	302
RFM-6_VBB	364	273	228	182	137
RFM-7_VCM-HD	1302	976	814	651	488
RFM-FORT-CMS	874	655	546	437	328
RFM-FORTA-CMS	874	655	546	437	328
RFM-DR-ADJ*	370 ~ 611	277 ~ 458	231 ~ 381	185 ~ 305	138 ~ 229
RFM-683-VCT-HD	370 ~ 611	277 ~ 458	231 ~ 381	185 ~ 305	138 ~ 229